



Diesel Generator Set Data

Manufacturer:	Jiangsu Starlight Generating Equipments Co.,Ltd
Set Type:	XG-75GF
Standby Output:	80KW/100KVA
Prime Output:	75KW/93.75KVA
Rated Current:	135 (A)
Rated Frequency:	50 (Hz)
Start-up time:	5~6 (s)
Power Factor:	0.8 (Lag)
Rated Voltage:	400/230 (V)

Standard Features

- ✓ Engine:Shanghai 6135D-3
- ✓ Radiator 40℃ max
- ✓ Fans are driven by belt, with safety guard
- ✓ 24V charge alternator
- ✓ Dry type air filter, fuel filter, oil filter
- ✓ Alternator: single bearing alternator
- ✓ IP22, insulation class H/H
- ✓ Main line circuit breaker
- ✓ Standard control panel
- ✓ Absorber
- ✓ muffler
- ✓ User manual





Diesel Engine Data

Manufacturer:	Shanghai Engine
Model:	6135D-3
Standby / Prime Power:	98KW/88.3KW
Rated Speed:	1500 (r/min)
Cycle:	4 stroke
Cylinder Arrangement:	6 in line
Displacement:	12L
Bore and Stroke:	135*140 (mm)
Compression Ratio:	16:1
Governor Type:	Mechanical
Start battery voltage:	24V DC

Air Intake System

Air Intake System:	Turbo
Min Intake Restriction:	10kpa
Burning Capacity:	5.63m ³ / min
Air Flow:	8.45m ³ / min

Exhaust System

Exhaust Gas Flow:	23.2m ³ / min
Exhaust Temperature:	≤650℃
Max Back Pressure:	6kpa

Fuel System

Fuel System:	Direct Injection
100%(Prime Power) Load:	210g/kwh

Oil System

Total Oil Capacity:	28.7L
Oil Consumption:	≤1.2g/kwh
Oil Pressure at Rated RPM:	0.30-0.35Mpa

Cooling System

Cooling Way:	Water-cooled
Total Coolant Capacity:	44L
Thermostat:	76-86
Max Water Temperature:	95℃



Alternator Data

	STARLIGHT
	KEPU/
Manufacturer:	STAMFORD/
	SIEMENS/
	MARATHON/
	ENGGA
Excitation Mode:	Brushless and self- exciting
Number of phase and Access Act:	3-phase 4-wire
Connecting Type:	“Y” type connecting
Alternator Capacity:	93.75KVA
Alternator Efficiencies:	95%
Overload:	(PRP) 110% load can run 1h
Protection Level:	IP22-IP23
Insulation Class, Temperature Rise:	H/H
Telephone Influence Factor (TIF):	<50
THF:	<2%
Altitude:	≤1000m

Genset Electrical Performance

Voltage Regulation:	≥±5%
Voltage Regulation, Stead State:	≤±1%
Sudden Voltage Warp (100% Sudden Reduce):	≤+25%
Sudden Voltage Warp (Sudden Increase):	≤-20%
Voltage Stable Time (100% Sudden Reduce):	≤6S
Voltage Stable Time (Sudden Increase):	≤6S
Frequency Regulation, Stead State:	≤5%
Frequency Waving:	≤1.5%
Sudden Frequency Warp (100% Sudden Reduce):	≤+12%
Sudden Frequency Warp (Sudden Increase):	≤-10%
Frequency Recovery Time (100% Sudden Reduce):	≤5S



FrequencyRecoveryTime(Sudden Increase):

≤5S

Options

Engine

Heater 2KW & 4KW
 Battery Charger 3.5A & 7A
 Water Separator
 Daily Fuel Tank
 Fuel Level Sensor

Alternator

Anti Condensation Heater
 Permanent Magnet Generator (PMG)
 Drop CT (For Paralleling)

Control System

Remote Control Panel
 Auto Transfer Switch (ATS)
 Paralleling System

Others

Rainproof Type
 Soundproof Type
 Trailer Type

Open Type

Overall Size

2600(mm)*950(mm)*1600(mm)

Weight

1850(kg)

Soundproof Type

Overall Size

3500(mm)*1400(mm)*2000(mm)

Weight

2800(kg)



Standard Control Panel



Starlight Standard Control Panel uses micro processing technique integrating digital, intelligent and network techniques which can carry out functions including auto start/stop, data measure, alarming. The controller uses LCD display, optional Chinese and English display interface with operation easy and reliable. It can be widely used in all types of generator automatic control system for compact structure, advanced circuits, simple connections and high reliability

Auto Module Control Panel



Auto Module Control Panel is the configuration for nobody on duty controlling generators. This kind of panel adopts auto module control system, with large LCD display to show the menu. Features: 6110 can receive remote output signal from ATS and realize auto start and stop of generators. 6310 can realize all functions of 6110, add RS232 interface which can communicate with PC to realize remote operation. 6410 Auto Mains Failure controller, can realize all functions of 6310, furthermore can detect ATS and control directly.

Auto Parallel Control Panel



This new automatic parallel system adopts intelligent modules, inserted and folded installed, no need the peripheral relay and logic circuit. The main switch adopts electronic breaker or frame breaker, combined together with the generator, which is very reliable. One generator, one panel. The panel can be used both for singly and parallel. It is only need to parallel generator with such panel when the capability needs to be enlarged in the future.